USB-7230/7250 USB 2.0-based Digital I/O Module

Getting Started



Package Contents

Your package should contain:

- USB-7230/7250
- Stand
- USB cable (2m)
- 2X 20-pin removable screw terminals
- Rail mount kit
- ADLINK All-in-One CD
- ADLINK All-IN-One CL
 Quick Start Guide
- (this document)

Installing the Driver

- 1. Download the latest UD-DASK driver & U-Test from: http://www.adlinktech.com/ and run.
- 2. Follow the installation instructions

Features

- USB 2.0, USB bus powered
- Programmable digital filter clears input channels
- Programmable DO/Relay initial status
- Up to 2500 VRMS isolation voltage

- · Removable screw terminals
- Lockable USB cable for secure connectivity
- Ready-to-use testing application
 (U-Test) included

Connecting the USB-7230/7250

- 1. Connect the USB-7230/7250 module to one USB 2.0 or 3.0 port on the computer using the included USB cable
- 2. The first time the USB-7230/7250 module is connected, a New Hardware message appears. It will take around 6 seconds to load the firmware. When complete, the LED indicator on the rear of the USB DAQ module changes from amber to green and the New Hardware message closes. The USB-7230/7250 module can now be located in the hardware Device Manager, as shown.

Je Action Yiew Help	
(中) 田 田 田 町 橋 登 長 街	
📸 test-PC	
> 🕂 Computer	
Disclay adapters	
A Human Interface Devices	
> con IDE ATA/ATAPI controllers	
> — Keyboards	
Mice and other pointing devices	
Network adapters	
D Other devices	
Ports (COM & LPT)	
Processors	
a sound, video and game controllers	
A B ANTERN SETAL BUS COMMENT	
ADLINK USBDAQ U7230	
Intel(R) 82801G (ICH7.5	
Intel(R) 82801G (ICH7 Family) US8 Universal Host Controller - 27C9	
 Intel(K) 82801G (ICH/ Family) USB Universal Host Controller - 27CA Intel(R) 92801G (ICH/ Family) USB Universal Host Controller - 27CR 	
Intel(R) 82801G (ICH7 Family) US82 Enhanced Host Controller - 27CC	
USB Root Hub	
*	
Device Manager	
Device Manager le Action View Help veltrani≣ Danna de Latable da	
Device Manager le Action Yew Holp ===== [] []	- 3 -
Device Menoger 	
Deve Manager He Adren Sper Belge n) (m) (m) (m) (m) (m) (m) (m) (m) (m) Spec Manager > ## Computer > # Computer > m) (m) (m) (m) (m) (m) (m) (m) (m) (m)	
Dereck tronger te daten Sper Urb αφ (m) (m) (1 m) (2 m) (4 m) (2 m) (4 m) π u α 2 m 1 m (2 m) (2 m) (4 m) (2 m) (4 m) 1 m (2 m) (4	
Devect Manager He Adres Yee Mark (m) (m) (m) (m) (m) (m) (m) (m) (m) (m) He Mark → (m)	
Conce Manager He dators year by the set of C is in the year of the year of the intervention of the year of the	
Devect tanger the Adma Spee Bob the Speet → Speet Speet → Spe	
Dereck Manger A dates year A dates year B dates C B dates C	
Dece Manager He Adres yee befor Dece Manager Dece Mana	
Devec Manager H afform Yeer Wey H Construction Yeer Wey H Construction Yeer H Afford Affo	
Dece Manager He Adren Sper He Mark Sper	
Devect Merger H actions time bible the actions time bible the actions time bible the actions the action bible the	
Derec Manyar A data Ser A data Ser B d	60)
Devect Merger H affen Signer Deve Lings Deve Lings	
Derec Manyar A data Series A data Series B data	
Devec Manager He dation year He dation year	
Device Manager Actions Same Big of Actions Same Big of Actions Same Big of Actions	
Deve Merger H affen Ser H af	
Carece Manager Beacher Manager Image: Section S	
Deck Many Beffer Second Second Second Second Second Second Second Sec	
Cence Manager March Manager Image: The CPC Image: The CPC <t< td=""><td></td></t<>	
Create Manager Beard In Sec.	
Decke Manager March Manager Image: Section Sect	
Create Manager Beacher Manager	
Deck Marger Marger Image: Second Secon	
Dece Marger Heard Marger Hea	
Devect Merger Arrow Server Markowski Server M	
Dece Many : A dem is of bit is defined in the second is defined in	

ADLINK



Pin Connections

Pin	Function	Pin	Function
20	VDD	40	DO15
19	DO7	39	DO14
18	DO6	38	DO13
17	DO5	37	DO12
16	DO4	36	DO11
15	DO3	35	DO10
14	DO2	34	DO9
13	DO1	33	DO8
12	DO0	32	IGND
11	IGND	31	IGND
10	CNT0	30	CNT1
9	CGND	29	COM
8	DI7	28	DI15
7	DI6	27	DI14
6	DI5	26	DI13
5	DI4	25	DI12
4	DI3	24	DI11
3	DI2	23	DI10
2	DI1	22	DI9
1	DI0	21	DI8

Pin	Function	Pin	Function
20	NO7	40	GND1
19	COM7	39	CNT1
18	NO6	38	GND0
17	COM6	37	CNT0
16	NO5	36	DI7L
15	COM5	35	DI7H
14	NO4	34	DI6L
13	COM4	33	DI6H
12	NC3	32	DI5L
11	NO3	31	DI5H
10	COM3	30	DI4L
9	NC2	29	DI4H
8	NO2	28	DI3L
7	COM2	27	DI3H
6	NC1	26	DI2L
5	NO1	25	DI2H
4	COM1	24	DI1L
3	NC0	23	DI1H
2	NO0	22	DIOL
1	COM0	21	DI0H

USB-7230 Pin Assignment

USB-7250 Pin Assignment

Quick Testing with U-Test

- 1. Connect the signal to be monitored and controlled to the USB-7230/7250
- 2. Launch the U-Test Utility from either the Start menu, or C:\ADLINK\U-test\U-Test.exe
- 3. Once the connected USB-7230/7250 is detected, configure the DI/O or counter settings and run to implement quick testing

Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction Image: Construction	
Image: Section 1 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Section 2 Image: Sectio	
Image Image <th< th=""><th></th></th<>	
•••••••••••••••••••••••••	
Output 0 1 2 3 4 5 6 7 Output 0 1 2 3 4 5 6 7 Output 0 1 2 3 4 5 6 7 Output 0 1 2 3 4 5 6 7 Imput 0 1 2 3 4 5 6 7 Imput 0 1 2 3 4 5 6 7 Imput 0 1 2 3 4 5 6 7 Imput 0 1 2 3 4 5 6 7 Imput 0 1 1 2 1 1 1 1 1 Imput 1 1 1 1 1 1 1 1 1 1 1 1 1 </td <td></td>	
Output 0 1 2 3 4 5 6 7 Output 0 1 2 3 4 5 6 7 Output 0 1 2 3 4 5 6 7 Prot 1 1 2 3 4 5 6 7 Prot 1 1 1 1 5 6 7 Output 0 0 1 1 1 1 1 1 Output 0 0 1<	
0 1 2 3 4 5 6 7 0 0 1 2 3 4 5 6 7 0 0 1 2 3 4 5 6 7 0 0 1 2 3 4 5 6 7 0 0 1 2 3 4 5 6 7 0 0 1 2 3 4 5 6 7 0 0 0 10 10 10 10 0 0 0 7 0 0 0 10 10 10 0 0 0 0 0 0 0 0 10 10 10 0	
Output orr orr <t< td=""><td></td></t<>	
Output OFF OFF<	
0 1 2 3 4 5 6 7 bipot 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 12 12 13 14 15 0 0 0 0 10 11 12 13 14 15 0 0 0 0 10 11 12 13 14 5 0 0 0 0 10 11 12 13 14 5 0 0 0 0 10 11 12 13 14 5 0 0 0 0 10 11 12 13 14 5 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	
0 1 2 3 4 5 6 7 ippet 0 0 0 13 13 14 15 0 0 0 13 13 14 15 0 0 13 12 13 14 15 0 0 13 12 13 14 15 0 0 13 12 13 14 15 0 0 13 14 15 15 15	
0 1 2 2 4 5 6 7 bipot 0 </td <td></td>	
Hight Image: Country Image: Country Image: Country Image: Country Output Output Image: Country Image: Country Image: Country Image: Country Output Output Image: Country Image: Country Image: Country Image: Country Image: Country Image: Country Image: Country Image: Country Image: Country	
Import	
0 0 10 11 12 13 14 15 0urgut orf orf orf orf orf orf orf orf 0 0 10 11 12 13 14 15 costs & Filter 0 10 11 12 13 14 15 costs & Filter 0 Inference Multitle jased jased	
0.0001 007 077<	
0 0 10 13 12 13 14 15 Output orp	
Output orr	
Oulput org org<	
OOS Event Counter Cost Eve	
0 9 10 11 12 13 14 15 C05 & Filter Digital Filter Exable Digital Filter Exable percent percent 0 Moment Pulse Width: percent percent percent	
0 9 10 12 23 14 15 COS & Riter Optical Filter Enable	
0 11 22 13 14 15 COS 5 Her Courter Digital Files Studies 0 Heiman Pulse Wolth:	
COS & Filter COS & Filter COS Event Counter Digital Place Studie 0 Meanum Pube Wolth:	
COS Event Counter Counter Page Final to Page	
O Meimum Puter Web: usec	
0 Minimum Pulse Width: 9990	

USB-7230 U-Test



USB-7250 U-Test



Web:http://www.adlinktech.comService:service@adlinktech.com

Tel: +886-2-8226-5877 Fax: +886-2-8226-3337

Copyright 2016 ADLINK Technology, Inc. Contents and specifications subject to change without notice.



Advance Technologies Automate the World